

SWITCHED-CAPACITOR CIRCUITS WITH REDUCED FINITE-GAIN EFFECT

* * * * *

CROSS-REFERENCE TO RELATED APPLICATIONS

[0001] Not applicable.

STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT

[0002] Not applicable.

BACKGROUND OF THE INVENTION

[0003] This invention is in the field of integrated circuits, and is more specifically directed to analog switched-capacitor circuits utilizing operational amplifiers.

[0004] A common building block in modern analog or mixed-signal analog
5 electronic circuits is the operational amplifier. As is fundamental in the art, operational amplifiers can be readily implemented into analog circuits for performing a wide range of functions, including analog multiplication, analog integration, active filtering, and analog-to-digital conversion, to name a few. These widely ranging functions derive from the ideal characteristics of an operational amplifier (or "op amp"), namely infinite
10 open loop gain, infinite input impedance, and zero output impedance. These ideal characteristics are used to advantage in conventional feedback op amp implementations, resulting in a "virtual" ground at the input (for finite voltage at the output, with infinite gain), and in the capability of the ideal op amp to generate high output current from zero input current.

15 [0005] An important class of circuits that are based on op amp realizations are switched-capacitor circuits. In general, switched-capacitor circuits involve the switching of charge among capacitors, for example from an input capacitor to a downstream

capacitor or capacitor network or to an op amp input. Switched-capacitor circuits use the transfer of charge among capacitors rather than the switching of current through resistors, to accomplish the circuit functions. Switched capacitor circuits are particularly attractive in modern integrated circuits, because of the ability of the manufacturing technology to physically construct high-quality capacitors in relatively small integrated circuit “chip” area; in contrast, integrated circuit resistors tend to occupy a great deal of chip area, and are difficult to fabricate with precise resistance values.

[0006] Figure 1 illustrates a first example of a conventional op amp circuit, specifically a sample-and-hold circuit. The function of this circuit is to drive an output voltage V_{out} that corresponds to a sample of an input voltage V_{in} . In this circuit, op amp 2 has its non-inverting input biased to ground and its inverting input connected to one plate of capacitor C at a node that is connected to ground through pass switch SB . The other plate of capacitor C is connected to receive input voltage V_{in} through pass switch SA , and the output of op amp 2 through pass switch SC . Pass switches SA , SB are clocked to be closed during clock phase Φ_1 , while pass switch SC is clocked to be closed during clock phase Φ_2 . Clock phases Φ_1 , Φ_2 are non-overlapping clock phases, as shown in Figure 1.

[0007] In operation, during “sample” clock phase Φ_1 , input voltage V_{in} charges capacitor C through closed pass switch SA , with pass switch SB connected to ground. During “hold” clock phase Φ_2 , pass switches SA , SB open, and pass switch SC closes. Because the non-inverting input of op amp 2 is at virtual ground for a finite output voltage V_{out} , and because pass switch SC has now connected capacitor C into the feedback loop, output voltage V_{out} equals the input voltage V_{in} (because of the inverting by op amp 2). Op amp 2 maintains this output voltage V_{out} until the next sample and hold period.

[0008] Figure 2 illustrates another conventional op amp circuit, which in this case is a switched-capacitor residual gain generator as used in a pipelined multiplying-digital-to-analog converter (MDAC) circuit. The function of the circuit of Figure 2 is to

derive an output signal V_{out} that depends upon the difference (i.e., residual) between an input voltage V_{in} and a reference voltage V_{DAC} . In this example in which the pipeline has 1 bit or 1.5 bits per stage, the output voltage V_{out} is intended to be twice the difference between input voltage V_{in} and a reference voltage $V_{DAC}/2$, where voltage

5 V_{DAC} is the unipolar full scale voltage of the pipelined MDAC. In this circuit, pass switches S1, S2 each receive input voltage V_{in} on one side, and are connected to another side to a first plate of respective capacitors C_A , C_B . Capacitors C_A , C_B are preferably of the same capacitance value. The other plates of capacitors C_A , C_B are connected together, and to an inverting input of op amp 4 via pass switch S5; these capacitor plates

10 are also connected to ground via pass switch S6. The first plate of capacitor C_A is connected to receive reference voltage V_{DAC} via pass switch S3, while the first plate of the capacitor C_B is connected to the output of op amp 4 via pass switch S4. Pass switches S1, S2, and S6 are clocked to be closed during clock phase Φ_1 , while pass switches S3, S4, and S5 are clocked to be closed during clock phase Φ_2 . Clock phases Φ_1 , Φ_2 are non-

15 overlapping clock phases, as shown in Figure 1.

[0009] In operation during "sample" clock phase Φ_1 , pass switches S1, S2, and S6 are closed, and pass switches S3, S4, S5 are open. Pass switches S1, S2 connect the input voltage V_{in} to capacitors C_A , C_B ; the opposite plates of capacitors C_A , C_B are connected to ground by the closed state of switch S6. Capacitors C_A , C_B thus both charge to input

20 voltage V_{in} during this clock phase. In clock phase Φ_2 , pass switches S1, S2, and S6 are open, and pass switches S3, S4, and S5 are closed. During this clock phase, the capacitor C_B becomes the feedback capacitor, and capacitor C_A receives the reference voltage V_{DAC} . To the extent that reference voltage V_{DAC} differs from input voltage V_{in} , charge sharing between capacitors C_A and C_B occurs. One can analyze the circuit by equating the sum

25 of the charge on capacitors C_A and C_B during clock phase Φ_1 with the sum of the charge on these capacitors during the next clock phase Φ_2 . In other words:

$$-V_{in}C_A - V_{in}C_B = -V_{out}C_B - V_{DAC}C_A \quad (1)$$

where the positive polarity sign of the charge on capacitors C_A , C_B points toward the inverting input of op amp 4, at virtual ground. Solving for output voltage V_{out} and assuming identical capacitance C for capacitors C_A and C_B :

$$V_{out} = 2(V_{in} - \frac{V_{DAC}}{2}) \quad (2)$$

5 In this manner, the circuit of Figure 2 generates an output that depends on a difference input signal. This residual gain stage is especially useful in multiplying DAC circuits, as known in the art.

[0010] Modern circuit design concepts and manufacturing technology have enabled the construction of conventional op amps that approach these ideal
10 characteristics, with very high gains, very high input impedance, and very low output impedance. To the extent that the actual realization of modern op amps fall short of the ideal characteristics, however, error is introduced into the circuit. For example, the necessarily finite gain of the op amp is typically reflected by a voltage at the op amp input that is not at ground, but is instead at a voltage inversely proportional to the finite
15 gain. This defeats the "virtual" ground assumption for the ideal op amp, and thus introduces error into the circuit. This source of error is typically referred to in the art as the "finite gain effect".

[0011] In addition, the switching speed of conventional op amps is also not instantaneous, which also introduces error into the circuit.

20 [0012] It is well known in the art that conventional op amp designs involve a tradeoff between switching speed and gain, such that a high switching speed can only be attained by sacrificing op amp gain, and vice versa. Highly precise analog circuits, such as multiplying DACs, thus involve this tradeoff between precision (typically reflected in the number of bits of precision in the conversion) and switching speed.

25 [0013] Because of these effects, the circuit application must either tolerate non-ideal op amp characteristics, or circuit techniques must be developed to reduce the effect

of these non-ideal characteristics. Previous circuit approaches to the reduction of finite gain effects are known in the art.

[0014] Nagaraj et al., "Reduction of the finite-gain effect in switched-capacitor filters", *Electron. Lett.*, Vol. 21 (July 1985), pp. 644-645; and Nagaraj et al., "Switched-
5 Capacitor Circuits with Reduced Sensitivity to Amplifier Gain", *IEEE Transactions on Circuits and Systems*, Vol. CAS-34, No. 5 (May 1987), disclose examples of these previous circuit approaches for reducing the finite gain effect. In these circuits, a correction for the finite gain effect is derived in a first, sample, clock phase, and then applied to the op amp in the second clock phase. These approaches each rely on the input voltage being
10 stable over both clock phases of operation. If the input voltage changes between phases, however, the correction is not accurate without including a third clock phase to obtain the exact correction. Accordingly, it is believed that the performance of these known op amp circuits is limited.

BRIEF SUMMARY OF THE INVENTION

[0015] It is therefore an object of this invention to provide a switched-capacitor operational amplifier circuit in which the finite gain effect is minimized.

[0016] It is a further object of this invention to provide such a circuit in which
5 modest op amp gain values can still provide excellent precision operation.

[0017] It is a further object of this invention to relax the tradeoff between op amp gain and switching speed, such that a higher speed op amp can be used in a precise application, such as a pipelined analog-to-digital converter (ADC).

[0018] It is a further object of this invention to provide such a circuit that can be
10 implemented as a sample-and-hold circuit, as a residual gain stage, and other op amp based circuits.

[0019] It is a further object of this invention to provide a pipelined ADC utilizing such a circuit, in which the clock phase timing of the pipelined stages is arranged to feed the correction values ahead to downstream stages, optimizing the performance of the
15 circuit.

[0020] Other objects and advantages of this invention will be apparent to those of ordinary skill in the art having reference to the following specification together with its drawings.

[0021] The present invention may be implemented into a switched-capacitor
20 circuit utilizing an operational amplifier ("op amp"), by including an additional capacitor coupled to an input of a fully differential op amp. Pass switches in the circuit are configured so that, during a first, sample, clock phase, a voltage corresponding to the differential at the op amp input from virtual ground is stored across the additional capacitor. In the succeeding amplify clock phase, this differential voltage is effectively
25 subtracted from the voltage appearing at the op amp input, compensating for the op amp finite gain. This implementation can be used in a sample-and-hold circuit, or in a

residual gain generator circuit such as used in multiplying digital-to-analog converter (MDAC) stages.

[0022] According to another aspect of the invention, a pipelined ADC is constructed using the inventive op amp circuits. Estimates of the op amp circuit outputs
5 are fed ahead to the next stages of the pipeline, and the clock phase timing of the pipelined stages is arranged to accept the estimates, enabling high performance operation.

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING

[0023] Figure 1 is an electrical diagram, in schematic form, of a conventional sample-and-hold circuit.

[0024] Figure 2 is an electrical diagram, in schematic form, of a conventional residual gain stage circuit.
5

[0025] Figure 3 is an electrical diagram, in schematic form, of a sample-and-hold circuit constructed according to the preferred embodiment of the invention.

[0026] Figures 4a and 4b are electrical diagrams, in schematic form, of the sample-and-hold circuit of Figure 3, according to the preferred embodiment of the invention, in first and second clock phases, respectively.
10

[0027] Figure 5 is an electrical diagram, in schematic form, of a residual gain stage circuit constructed according to the preferred embodiment of the invention.

[0028] Figures 6a and 6b are electrical diagrams, in schematic form, of the residual gain stage circuit of Figure 5, according to the preferred embodiment of the invention, in first and second clock phases, respectively.
15

[0029] Figure 7 is an electrical diagram, in block form, of a pipelined ADC constructed according to the preferred embodiment of the invention.

[0030] Figure 8 is a timing diagram illustrated the phased operation of the pipelined ADC of Figure 7, according to the preferred embodiment of the invention.

DETAILED DESCRIPTION OF THE INVENTION

[0031] The present invention will be described in connection with its preferred embodiment, namely as implemented into various circuits used in a pipelined analog-to-digital converter (ADC). This particular implementation is described because it is contemplated that this invention is especially beneficial in such an application. However, it is also contemplated that this invention can be advantageously used in a wide range of operational amplifier circuits. Accordingly, it is to be understood that the following description is provided by way of example only, and is not intended to limit the true scope of this invention as claimed.

10 [0032] Referring now to Figure 3, sample-and-hold circuit 20 constructed according to a preferred embodiment of the invention will now be described. As shown in Figure 3, sample-and-hold circuit 20 includes operational amplifier ("op amp") 15, which has its non-inverting input at ground, and its inverting input connected to a node N2 connected to one side of capacitor C_3 and one side of pass switch 18. Circuit 20 according to this embodiment of the invention is single-ended, but in its practical implementation would be fully differential in order to receive input voltage V_{in} and its negative $-V_{in}$; the output of circuit 20 is output voltage V_o , driven by the output of op amp 15. The positive input voltage V_{in} is received by capacitor C_4 at node N+ through pass switch 14; an opposite plate of capacitor C_4 is connected to node N1, as is capacitor C_3 . Node N1 is selectably connected to ground through pass switch 16. A feedback loop is formed by pass switch 24, which connects node N+ to the output of op amp 15.

[0033] The negative input voltage $-V_{in}$ is received by capacitor C_1 , at node N-, via pass switch 12. Node N- is selectably connected to ground through pass switch 22. Capacitor C_1 is also connected to capacitor C_2 , and to node N2 via pass switch 18. Capacitor C_2 is connected to the output of op amp 15 via pass switch 19, and both sides of capacitor C_2 can be grounded by pass switches 26, 28.

[0034] Pass switches 12, 14, 16, 18, 19, 22, 24, 26, 28 are constructed by transistors, according to the available technology used to realize the integrated circuit including sample-and-hold circuit 20. For example, if complementary metal-oxide-semiconductor (CMOS) technology is available, each of pass switches 12, 14, 16, 18, 19, 22, 24, 26, 28 may be constructed by the conventional arrangement of parallel-connected p-channel and n-channel transistors, with the gates of these transistors receiving complementary control signals. In circuit 20 according to this embodiment of the invention, pass switches 12, 14, 16, 18, 19 are controlled to be closed during clock phase Φ_1 (and open otherwise) while pass switches 22, 24, 26, 28 are controlled to be closed during clock phase Φ_2 (and open otherwise). Clock phases Φ_1 and Φ_2 are non-overlapping clock signals, as conventional in the art for switched-capacitor circuits, as mentioned above.

[0035] Capacitors C_1 through C_4 are conventional capacitor devices, also constructed according to the available technology used to realize the integrated circuit including sample-and-hold circuit 20. For example, it is contemplated that capacitors C_1 through C_4 will be conventional MOS capacitors. The particular capacitance values will depend upon the specific circuit design; for ease of explanation, this description will assume that capacitors C_1 through C_4 will all have the same capacitance value as one another.

[0036] In operation, sample-and-hold circuit 20 uses clock phase Φ_1 as a "sample" phase, and clock phase Φ_2 as a "hold" phase. Figure 4a illustrates circuit 20 during clock phase Φ_1 , in which pass switches 12, 14, 16, 18, 19 (not shown) are closed and pass switches 22, 24, 26, 28 (not shown) are open. In this clock phase, input voltages V_{in} , $-V_{in}$ are stored across capacitors C_4 , C_1 , respectively. Because of the feedback connection of capacitor C_2 (assuming that it has the same capacitance as capacitor C_1), the output voltage V_o closely resembles input voltage V_{in} because of the application of negative input voltage $-V_{in}$ to the inverting input of op amp 15. Capacitor C_1 stores

voltage V_{in} during this sample clock phase Φ_1 , in the conventional manner for sample-and-hold circuits.

[0037] Ideally, in clock phase Φ_1 , node N2 at the inverting input to op amp 15 is at virtual ground, due to the infinite gain of op amp 15. Of course, in practice, the gain of op amp 15 is not infinite but is instead a finite gain A_0 , and as such the voltage at node N2 in clock phase Φ_1 is not at ground (but is instead at a voltage $\frac{V_o}{A_0}$). According to this preferred embodiment of the invention, this voltage $\frac{V_o}{A_0}$ at node N2 is stored across capacitor C_3 , since node N1 is at ground.

[0038] The state of sample-and-hold circuit 20 at clock phase Φ_2 is shown in Figure 4b, in which pass switches 22, 24, 26, 28 (not shown) are closed and pass switches 12, 14, 16, 18, 19 (not shown) are open. During this clock phase Φ_2 , capacitors C_1 and C_2 are discharged to ground. The input voltage V_{in} that was stored across capacitor C_4 is applied to the non-inverting input of op amp 15 (as a negative voltage, since node N1 was previously grounded). However, capacitor C_3 is in series with capacitor C_4 and, as discussed above, is storing voltage $\frac{V_o}{A_0}$ from clock phase Φ_1 . This voltage $\frac{V_o}{A_0}$ is opposite in polarity from the stored input voltage V_{in} , and as such is effectively subtracted from sampled input voltage V_{in} . In effect, the non-zero voltage $\frac{V_o}{A_0}$ due to the finite gain of op amp 15 is applied as a correction to the input of op amp 15 in the hold phase, thus compensating for the finite gain effect of non-ideal op amp 15.

[0039] The correction applied by sample-and-hold circuit 20 resulting from the finite gain effect is especially accurate, relative to known prior techniques, because the correction voltage $\frac{V_o}{A_0}$ is derived from the same voltage that is then being sampled in the sample clock phase Φ_1 . According to this embodiment of the invention, this correction

voltage is derived from the complement to the input voltage V_{in} being sampled, in this fully differential implementation.

[0040] The effect of the finite gain effect correction provided by sample-and-hold circuit 20 according to this embodiment of the invention is to reduce the circuit error to a level that would be available from an op amp having much higher gain than op amp 15 actually has. In other words, from a precision standpoint, sample-and-hold circuit 20 operates as though the gain of op amp 15 is much higher than it actually is. The effective gain, from an error standpoint, can be calculated from a charge analysis of circuit 20. Considering time n as clock phase Φ_2 , and time $n+1$ as clock phase Φ_1 , the sum of the charges Q_1 , Q_2 , Q_3 on respective capacitors C_1 , C_2 , C_3 in clock phase Φ_1 equals the charge Q_3 on capacitor C_3 in clock phase Φ_2 (capacitors C_1 , C_2 being grounded as shown in Figure 4b), as follows:

$$Q_1(n+1) + Q_2(n+1) + Q_3(n+1) = Q_3(n) \quad (3)$$

Positive sign polarity is toward the inverting input of op amp 15. Expanding this charge equation according to the voltages and capacitances of the circuit:

$$C_1 V_{in}(n+1) - \frac{V_0(n+1)}{A_0} (C_1 + C_2 + C_3) - V_0(n+1) C_2 = \frac{V_0(n)}{A_0} C_3 \quad (4)$$

In terms of the voltage across capacitor C_3 in clock phase Φ_1 :

$$V_{C3}(n+1) = V_{in}(n+1) \frac{C_1}{A_0 C_2 + C_1 + C_2 + C_3} - V_0(n) \frac{C_3}{A_0 (A_0 C_2 + C_1 + C_2 + C_3)} \quad (5)$$

Because the voltage across C_4 is, of course, $V_{in}(n+2)$, for the next clock phase Φ_2 can be derived from:

$$V_0(n+2)\left(1 + \frac{1}{A_0}\right) = V_{in}(n+1) + V_{C3}(n+1) \quad (6)$$

which can be expressed as:

$$V_0(n+2) = \frac{A_0}{A_0+1} \left[V_{in}(n+1) \left(1 + \frac{C_1}{A_0 C_2 + C_1 + C_2 + C_3} \right) - V_0(n) \frac{C_3}{A_0 (A_0 C_2 + C_1 + C_2 + C_3)} \right] \quad (7)$$

As discussed above, in this example the capacitances C_1 , C_2 , C_3 are equal. This equation (7) can thus be simplified to:

$$V_0(n+2) = V_{in}(n+1) \frac{A_0}{A_0+1} \frac{A_0+4}{A_0+3} - V_0(n) \frac{A_0}{(A_0+1)(A_0^2+3A_0)} \quad (8)$$

[0041] One can compute the finite gain error for a given op amp gain A_0 from this equation (8). For example, for a gain A_0 of 60 dB, or 1000, the evaluation of equation (8) is:

$$V_0(n+2) = V_{in}(n+1)0.9999970 - V_0(n)9.960129 \cdot 10^{-7} \quad (9)$$

10 For a 60 dB gain op amp utilized in a conventional sample-and-hold circuit, the output voltage $V_0(n+2)$ would be:

$$V_0(n+2) = V_{in}(n+1) \frac{A_0}{A_0+1} = V_{in}(n+1) \cdot 0.999000999 \quad (10)$$

Accordingly, in this example of the preferred embodiment of the invention, sample-and-hold circuit 20 behaves, from the standpoint of finite gain error, as the equivalent of a

conventional sample-and-hold circuit in which the op amp has a finite gain A_0 of 110 dB, or 334,671. As a result, a lower gain op amp can be used in sample-and-hold circuit 20 according to this embodiment of the invention without loss of precision; conversely, op amp 15 of a higher switching speed (and thus lower gain) can be used to provide higher speed performance without a loss of precision due to the necessarily lower gain of such an op amp. This invention thus provides greater freedom for the designer of circuits utilizing sample-and-hold circuit 20.

[0042] Other advantages are also provided by sample-and-hold circuit 20 according to this preferred embodiment of the invention. One such additional advantage is because capacitor C_3 also samples low frequency noise, effectively providing a $1/f$ noise cancellation. In addition, any parasitic capacitance at the output of op amp 15 is precharged during clock phase Φ_1 ; while op amp 15 must provide a small amount of charge in the transition from clock phase Φ_1 to clock phase Φ_2 , the response of the output of op amp 15 is much faster than in conventional circuits. In addition, as will be described in further detail below, output voltage V_o driven by op amp 15 at the end of clock phase Φ_1 is a good approximation of the eventual output voltage V_o , and may be fed ahead to later stages in a pipelined circuit utilizing sample-and-hold circuit 20.

[0043] Other op amp circuits can also take advantage of this invention. Figure 5 illustrates residual gain generator circuit 30 constructed according to a preferred embodiment of the invention. As discussed above relative to the conventional residual gain generator shown in Figure 2, residual gain generator circuit 30 of Figure 5 is for generating an output voltage V_o that is two times the difference between an input voltage V_{in} and a reference voltage $V_{DAC}/2$.

[0044] Residual gain generator circuit 30 is based on op amp 25, which has its non-inverting input at ground, and its inverting input connected to node N22. Input voltage V_{in} is applied to one side of capacitor $C14$ via pass switch 34, and to one side of capacitor $C15$ via pass switch 35; capacitors $C14$, $C15$ are connected to one plate of capacitor $C13$ at node N21, and the opposite plate of capacitor $C13$ is connected to the

inverting input of op amp 25 at node N22. One feedback loop of op amp 25 is connected to capacitor C15 via pass switch 44. Negative input voltage $-V_{in}$ is applied to capacitor C11 via pass switch 33 at a plate that is selectably grounded by pass switch 42; the opposite plate of capacitor C11 is connected to node N22 via pass switch 37. Another
5 feedback loop from the output of op amp 25 is through capacitor C12 and pass switches 33, 37; pass switches 46, 48 selectably ground both plates of feedback capacitor C12.

[0045] The reference voltage V_{DAC} is applied to capacitor C14 via pass switch 43. Conversely, negative reference voltage $-V_{DAC}$ is applied to one plate of capacitor C16 via pass switch 31; this plate is selectably grounded by pass switch 41. The opposite plate of
10 capacitor C16 is connected to capacitor C11, and is also connected to node N22 via pass switch 37.

[0046] The construction of pass switches 31 through 39 and 41 through 48 is preferably according to conventional pass gate or pass transistor techniques, for the appropriate manufacturing technology. For example, according to CMOS technology,
15 each of pass switches 31 through 39 and 41 through 48 are preferably parallel-connected p-channel and n-channel MOS transistors, with gates receiving complementary signals. Capacitors C11, C12, C13, C14, C15 are also preferably constructed according to the available integrated circuit manufacturing technology, such as by way of MOS capacitors. The capacitance values of capacitors C11, C12, C13, C14, C15 are selected by
20 the designer according to the desired circuit performance, and according to the gain desired from residual gain generator circuit 30. Typically, capacitors C11 and C16 will have the same capacitance as one another, as will capacitors C14 and C15. It is contemplated that those skilled in the art having reference to this specification will be readily able to select the appropriate capacitance values.

25 [0047] Pass switches 31, 32, 33, 34, 35, 36, 37, 39 are clocked to be closed during clock phase Φ_1 and open otherwise, while pass switches 41, 42, 43, 44, 46, 48 are clocked to be closed during clock phase Φ_2 and open otherwise. As before, clock phases Φ_1 and

Φ_2 are non-overlapping clock signals, as conventional for switched-capacitor circuits such as residual gain generator circuit 30.

[0048] In operation, residual gain circuit 30 generates an error voltage corresponding to the finite gain error from op amp 25 in the sample phase (clock phase Φ_1), and stores this error voltage across capacitor C13. This error voltage is applied to the inverting input of op amp 25, subtracted from the difference voltage, in clock phase Φ_2 , thus compensating for the finite gain error.

[0049] Figure 6a illustrates residual gain generator circuit 30 during clock phase Φ_1 , with none of pass switches 31, 32, 33, 34, 35, 36, 37, 39, 41, 42, 43, 44, 46, 48 shown, for clarity. In clock phase Φ_1 , input voltage V_{in} is sampled and stored on capacitor 14, and also on capacitor C15. Also during this clock phase Φ_1 , an error voltage is developed across capacitor C13. In the ideal case, the voltage at node N22, at the inverting input of op amp 25, would be at ground (i.e., "virtual" ground) because of the ideal infinite gain of op amp 25, and the voltage across capacitor C13 would be zero (because node N21 is also at ground). But because op amp 25 has a finite gain A_0 , the voltage at node N22 is not at zero, but is instead at a voltage $\frac{V_o}{A_0}$. The application of negative reference voltage $-V_{DAC}$ to capacitor C16, negative input voltage $-V_{in}$ to capacitor C11, and input voltage V_{in} to capacitor C15, along with the connection of capacitor C12 in the feedback loop, effectively produces the same input condition to op amp 25 as in normal operation, as will become evident from the following description of the operation of residual gain generator circuit 30 during clock phase Φ_2 , as shown in Figure 6b. The error voltage $\frac{V_o}{A_0}$ is stored across capacitor C13, in clock phase Φ_1 .

[0050] In clock phase Φ_2 , pass switches 41, 42, 43, 44, 46, 48 are closed and pass switches 31, 32, 33, 34, 35, 36, 37, 39 are open. The resulting circuit arrangement during clock phase Φ_2 is shown in Figure 6b. Capacitors C11, C16, C12 are all discharged to ground. The feedback path from the output of op amp 25 is connected through

capacitor C15, which received input voltage V_{in} in clock phase Φ_1 ; reference voltage V_{DAC} is applied to capacitor C14, which also receive input voltage V_{in} in clock phase Φ_1 . Accordingly, the voltage at node N21 in clock phase Φ_2 is a difference voltage that is developed in similar fashion as equation (1), namely as twice the input voltage V_{in} less
5 the reference voltage V_{DAC} . The error voltage $\frac{V_o}{A_o}$ stored across capacitor C13 in clock phase Φ_1 is effectively subtracted from this difference voltage by the series connection of capacitor C13 between nodes N21 and N22, thus correcting for the finite gain error of op amp 25.

[0051] According to this embodiment of the invention, the finite gain correction
10 applied in residual gain generator circuit 30 has improved accuracy over conventional circuits, because the same input voltage V_{in} that is sampled in the sample clock phase Φ_1 is used (in the form of the negative input voltage $-V_{in}$) in generating the correction error voltage at capacitor 13. The residual gain output voltage V_o is therefore quite accurate.

[0052] This accuracy depends upon a stable reference voltage V_{DAC} over both
15 clock phases Φ_1 and Φ_2 . In some high-speed applications, this assumption may not be exactly accurate. For example, in a conventional ADC circuit, the reference voltage V_{DAC} is an output voltage resulting from a digitized version of the input voltage V_{in} itself. This digitized input may not be ready at the time that the input voltage V_{in} is sampled. One could wait for an additional cycle of the sample and hold clocks, but this would
20 insert latency into the system. According to a preferred embodiment of the invention, as implemented into a pipelined ADC, an estimate of the reference voltage V_{DAC} is sampled by residual gain generator 30; while this estimate may not be completely accurate, it is contemplated that other circuitry can be used to minimize the error resulting from the feeding-ahead of the reference voltage V_{DAC} , as will now be described with reference to
25 Figure 7.

[0053] Pipelined ADC 50 may be implemented into a stand-alone integrated circuit, or alternatively may be implemented into an integrated circuit that also includes

other functions. For example, pipelined ADC 50 may be implemented into a single-chip system for processing signals, such as a single-chip mobile telephone handset device or the like. In any event, conventional control, power, and clock circuitry (not shown in Figure 7) will be provided in the integrated circuit into which pipelined ADC 50, to provide the appropriate control functions, power supply and reference voltages, and system clock signals for pipelined ADC 50 and the other functions in the integrated circuit. According to this preferred embodiment of the invention, as shown in Figure 7, clock circuit 41 generates non-overlapping clock phases Φ_1 and Φ_2 , which control pipelined ADC 50 as will be described below.

[0054] Pipelined ADC 50 according to this preferred embodiment of the invention includes sample-and-hold circuit 20, which receives an input analog signal ANA_IN. Sample-and-hold circuit 20 is preferably constructed according to the preferred embodiment of this invention described above relative to Figure 3, and as such samples the state of input analog signal ANA_IN and provides a held analog level corresponding to the sampled signal at its output. Sample-and-hold circuit 20 operates in response to clock phases Φ_1 and Φ_2 , with clock phase Φ_1 corresponding to the sample phase, and clock phase Φ_2 corresponding to the operation, or "hold", phase. The output of sample-and-hold circuit 20 is applied to a first one of a sequence of multiple pipeline stages, each stage including a residual gain generator 30, an analog-to-digital converter (ADC) 44, and a digital-to-analog converter (DAC) 42. Pipeline stages of this construction are typically referred to as multiplying digital-to-analog converter (MDAC) stages. In Figure 7, three such stages are specifically shown; the other stages following the first three are implied.

[0055] In the first pipeline stage, residual gain generator 30₀ and first analog-to-digital converter (ADC) 44₀ receive the output of sample-and-hold circuit 20. Residual gain generator 30₀, as well as residual gain generators 30₁, 30₂, etc. in the later pipeline stages, are preferably constructed according to the preferred embodiment of the invention, as described above relative to Figure 5. As such, the output of sample-and-

hold circuit 20 is received as input voltage V_{in} (and its complement, negative input voltage $-V_{in}$) to residual gain generator circuit 30₀. According to the preferred embodiment of the invention, the clock phasing of residual gain generator circuit 30₀ is opposite from that of sample-and-hold circuit 20, in that clock phase Φ_2 is the sample clock phase for gain generator circuit 30₀ (corresponding to clock phase Φ_1 in the description relative to Figures 5 and 6a), and clock phase Φ_1 is the operating clock phase for gain generator circuit 30₀ (corresponding to clock phase Φ_2 in the description relative to Figures 5 and 6b). This reversal of the clock phases provides excellent performance, as will be described in further detail below.

[0056] According to the preferred embodiment of the invention, ADC 44₀ is preferably a conventional 1.5 bit analog-to-digital converter circuit, or threshold comparator, as known in the art. As such, ADC 44₀ compares the analog signal at its input (from sample-and-hold circuit 20, in this example) to a positive threshold $V+$ and a negative threshold $V-$, and generates a two bit digital value at its output in response to this comparison. For example, the output state 00 may indicate that the input voltage is lower than both of the thresholds $V+$ and $V-$, the state 01 may indicate that the input voltage is higher than negative threshold $V-$ but lower than positive threshold $V+$, and the state 11 may indicate that the input voltage is higher than both of the thresholds $V+$ and $V-$. In this first stage, ADC 44₀ samples the input voltage in clock phase Φ_1 and performs the comparison and outputs the digital value in clock phase Φ_2 . This digital output from ADC 44₀ is applied to the input of digital-to-analog converter (DAC) stage 42₀, as shown in Figure 7. In addition, the digital value output by ADC 44₀ corresponds to a bit of the digital result (namely the most significant bit, for first stage ADC 44₀), and is applied to digital correction circuit 45.

[0057] DAC stage 42₀ in this first pipeline stage is a conventional 1.5 bit DAC, in that it generates an analog level responsive to the digital level received at its input. In DAC stage 42₀ of this first stage of ADC circuit 50, clock phase Φ_2 is the sample clock phase and clock phase Φ_1 is the operating clock phase. Accordingly, the digital output

of ADC 44₀ is latched in clock phase Φ_2 and the output level is generated in clock phase Φ_1 , in this first pipeline stage. According to this embodiment of the invention, the output signal from DAC stage 42₀ is reference voltage V_{DAC} , and preferably also its complement, negative input voltage $-V_{DAC}$.

5 [0058] The output reference voltages V_{DAC} , $-V_{DAC}$ generated by DAC stage 42₀ are received by residual gain generator 30₀, along with the input voltages V_{in} , $-V_{in}$ from sample-and-hold circuit 20, as mentioned above. In this first pipeline stage, according to this preferred embodiment of the invention and as mentioned above, clock phase Φ_2 is the sample clock phase for residual gain generator circuit 30₀, and clock phase Φ_1 is the
10 operating clock phase. Accordingly, the input voltage V_{in} from sample-and-hold circuit 20 is sampled, and the error voltage across capacitor C13 (Figure 5) is developed from negative input voltage $-V_{in}$ and negative reference voltage $-V_{DAC}$ during clock phase Φ_2 . The output voltage V_o , corresponding to the residual between input voltage V_{in} and reference voltage V_{DAC} from DAC 42₀ is then generated in clock phase Φ_1 , and applied as
15 the input voltage V_{in} to residual gain generator circuit 30₁ and ADC 44₁ in the second pipeline stage.

[0059] The residual output from residual gain generator circuit 30₀ corresponds to the residual remainder between the original input voltage ANA_IN, once the most significant bit is extracted (by ADC 44₀). In this embodiment of the invention, this
20 residual value is then again compared to a threshold value by ADC 44₁ to generate the next most significant bit of the converted digital output signal, and the residual is forwarded to the next pipeline stage for extraction of the next most significant bit, and so on. The final residual output from a last pipeline stage of ADC 50 is applied to digital correction circuit, along with the digital bit values from each of ADC's 44 in the pipeline
25 stages, to generate the digital output value DIG_OUT.

[0060] As mentioned above, sample-and-hold circuit 20 of ADC 50 samples the input signal ANA_IN during clock phase clock Φ_1 , and outputs input voltage V_{in} to the first residual gain generator circuit 30₀ during clock phase Φ_2 . This operation is

illustrated in Figure 8. As described above relative to Figure 3, however, the output of sample-and-hold circuit 20 during its sample clock phase Φ_1 is a reasonably good approximation of the eventual output voltage (without the finite gain error correction from capacitor C_3 , but from which this finite gain error is determined). Because of its 1.5
5 bit construction, some amount of error in the input voltage applied to ADC 44₀ can be tolerated. In ADC 50 according to this embodiment of the invention, therefore, ADC 44₀ samples the output of sample-and-hold circuit 20 in the same clock phase Φ_1 as the sample phase of sample-and-hold circuit 20 itself.

[0061] In the next clock phase, namely clock phase Φ_2 , sample-and-hold circuit
10 20 presents its precise output voltage, and ADC 44₀ presents a digital value corresponding to the comparison of the voltage that it sampled in the previous clock phase Φ_1 to the threshold V_+ , V_- . DAC 42₀ samples this estimated voltage and generates its corresponding analog output voltage V_{DAC} (and negative reference voltage $-V_{DAC}$) to residual gain generator 30₀, for sampling during clock phase Φ_2 . Also during this clock
15 phase Φ_2 , residual gain generator 30₀ samples the input voltage V_{in} (and negative input voltage $-V_{in}$). In the next clock phase Φ_1 , residual gain generator 30₀ in the first pipeline stage of pipelined ADC 50 generates its output voltage V_o , which is applied to residual gain generator 30₁ as the true residual voltage. Residual gain generator 30₁ samples this voltage during this clock phase Φ_1 .

20 [0062] As described above relative to Figures 5 and 6a, residual gain generator 30₀ generates an output voltage V_o during its sample phase (clock phase Φ_2) that is a reasonable approximation of the eventual output voltage V_o ; this approximation is used to derive the finite gain error voltage that is stored across its capacitor C_{13} . According to this preferred embodiment of the invention, ADC 44₁ in the second pipeline stage of
25 pipelined ADC 50 samples this approximated output voltage V_o during this same clock phase Φ_2 . Similarly as in the operation of ADC 44₀, which generates its result from an approximation of the output of sample-and-hold circuit 20, ADC 44₁ utilizes this approximate output voltage from residual gain generator 30₀ for its operations. This

ensures that good approximation of voltage V_{DAC} is present at residual gain generator 30₁ in this second pipeline stage at the next clock phase Φ_1 , at which the time true residual voltage from residual gain generator 30₀ is present.

[0063] As evident from Figure 7, the phased operation of each of the pipeline stages alternates from stage to stage. In this example, each ADC stage 44 in the first and third stages (and all subsequent odd-numbered stages) samples its input in clock phase Φ_1 and performs the comparison and outputs a digital value in clock phase Φ_2 . Conversely, each ADC stage 44 in the second stage (and all subsequent even-numbered stages) samples its input in clock phase Φ_2 and performs the comparison and output in clock phase Φ_1 . Each residual gain generator circuit 30 in the first and third stages (and all subsequent odd-numbered stages) samples its inputs and generates an approximate output voltage in clock phase Φ_2 and generates the accurate output residual voltage in clock phase Φ_1 , while each residual gain generator circuit 30 in the second (and all subsequent even-numbered stages) samples its inputs and generates an approximate output voltage in clock phase Φ_1 and generates the accurate output residual voltage in clock phase Φ_2 . This alternating clock phasing ensures minimum latency through pipelined ADC 50.

[0064] This operation of pipelined ADC 50 continues through each of the pipelined stages. Following the last pipelined stage, the output of the last residual gain generator is applied to digital correction circuit 45, along with the digital values from each of the ADC stages 44. Digital correction circuit 45 is a conventional circuit as commonly known in the art for applying comparator digital correction in an ADC. Because the values generated by DAC stages 42 are not from the actual sampled value of the preceding stage but rather from the predictive values, these values may contain an error. However, because this error is not intrinsically caused by the DAC stage 42 but rather by the input presented to the comparators in its pipeline stage, that error can be referred to the input of the comparators (ADC stages 44) and will be corrected by circuit 45 in the conventional manner. Digital error correction circuit 45 operates by time

aligning and summing the outputs of ADC stages 44. As known in the art, if the digital output from any one of a more significant pipeline stage is in error, the resulting residue that is passed to less significant pipeline stages (assuming no over-ranging of these later stages) will produce a digital output code from the less significant pipeline stages that, when added to the erroneous more significant digital output by digital error correction circuit 45, will still produce the correct overall digital output from ADC 50. A description of the operation of a conventional digital error correction circuit 45 is provided in "Understanding Pipelined ADCs", *Application Note 383* (Dallas Semiconductor, March 1, 2001), available at http://www.maxim-ic.com/appnotes.cfm/appnote_number/383. It is contemplated that as many as ten or more such pipeline stages will often be implemented, but of course the number of such pipeline stages will depend upon the desired precision of the digital output signal DIG_OUT.

[0065] According to the preferred embodiments of the invention, therefore, the effects of finite op amp gain are greatly eliminated from switched-capacitor circuits, such as the sample-and-hold and residual gain generator circuits described above. In effect, the precision of these circuits resembles that of circuits having op amps with much higher open loop gain values. Considering the well-known tradeoff between switching speed and open loop op amp gain, this invention permits higher switching speed op amps to be used in these switched-capacitor circuits, without the expected cost in precision or increased error that would otherwise result from faster, but lower gain, op amps.

[0066] In addition, this invention provides a highly efficient pipelined analog-to-digital converter, in which estimates of previous voltage levels, from sample phases, are used in downstream residual gain generator circuits, greatly reducing the latency of each pipelined stage. To the extent that these estimates result in error in the output, it is contemplated that conventional digital correction can account for such error.

[0067] While the present invention has been described according to its preferred embodiments, it is of course contemplated that modifications of, and alternatives to, these embodiments, such modifications and alternatives obtaining the advantages and benefits of this invention, will be apparent to those of ordinary skill in the art having
5 reference to this specification and its drawings. It is contemplated that such modifications and alternatives are within the scope of this invention as subsequently claimed herein.